



Alkaline Cell For Electronic Device

With its comprehensive product range, alkaline button cells are used to power various kinds of small portable electronic devices, including electronic toys, calculators and remote controls.

Features

- ★ Deliver power required for small electronic devices
- ★ Comprehensive product range
- ★ Multi applications


Major Applications

Electronic toys, calculators, remote controls




Standard Packs

Mercury Free Series



A76-C1 1.5V



A76-C2 1.5V




A76-C5 1.5V


Mercury Free Series
available models

Model No.	Packing Type
186	C1 1pc/card
	C5 5pcs/card
189	C1 1pc/card
	C5 5pcs/card
192	C1 1pc/card
	C5 5pcs/card
PX625A	C1 1pc/card
	C5 5pcs/card
A76	C1 1pc/card
	C2 2pcs/card
	C5 5pcs/card

Low Mercury Series



A76-C1 1.5V



A76-C2 1.5V



A76-C5 1.5V



A76-C10 1.5V

Low Mercury Series
available models

Model No.	Packing Type
164	C5 5pcs/card
	C10 10pcs/card
177	C5 5pcs/card
	C10 10pcs/card
186	C1 1pc/card
	C5 5pcs/card
189	C1 1pc/card
	C5 5pcs/card
191	C1 1pc/card
	C5 5pcs/card
192	C1 1pc/card
	C5 5pcs/card
PX625A	C1 1pc/card
	C5 5pcs/card
A76	C1 1pc/card
	C5 5pcs/card
A76	C1 1pc/card
	C10 10pcs/card

Alkaline Cells (Mercury Free Series)



Model No.	Dimension (mm)		Voltage (V)	Nominal Capacity (mAh)	Cross Reference				
	Diameter	Height			IEC	JIS	Eveready	Varta	Duracell
A76	11.6	5.4	1.5	110	LR44	LR44	A76Z	V13GA	LR44
186	11.6	4.2	1.5	70	LR43	LR43	186	V12GA	LR43
189	11.6	3.05	1.5	44	LR54	LR1130	189	V10GA	LR54
192	7.9	3.6	1.5	24	LR41	LR41	192Z	V3GA	—
PX625A	15.6	5.95	1.5	190	LR9	LR9	E625G	V625U	625A

Alkaline Cells (Low Mercury Series)



Model No.	Dimension (mm)		Voltage (V)	Nominal Capacity (mAh)	Cross Reference				
	Diameter	Height			IEC	JIS	Eveready	Varta	Duracell
A76	11.6	5.4	1.5	110	LR44	LR44	A76Z	V13GA	LR44
164	6.8	2.15	1.5	8	LR60	—	—	—	LR620
177	6.8	2.6	1.5	12	LR626	LR626	—	—	—
186	11.6	4.2	1.5	70	LR43	LR43	186	V12GA	LR43
189	11.6	3.05	1.5	44	LR54	LR54	189	V10GA	LR54
191	11.6	2.05	1.5	24	LR55	LR55	191	V8GA	—
192	7.9	3.6	1.5	24	LR41	LR41	192Z	V3GA	—
PX625A	15.6	5.95	1.5	190	LR9	LR9	E625G	V625U	625A